

iBonus Terminal™

Admin Operation Quick Reference Card

- Initialize Member Card
- Configure Terminal Mode
- Mode of Expiry
- Creating Staff Card
- Blacklist Staff Card
- Network Settings
- Administrator Password
- System Reset and Shutdown
- Set Customer ID
- Deregister Terminal
- Set Bonus Rate
- Internationalization
- Master Card

Initialize Member Card

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 1 to select the Init Card menu. The number of card formatting quota and the card ID of the next formatted card is shown on the screen.	Quota: 100 ID: 0000000100
Present a blank new card. Do not pick up the card until the writing is finished.	Writing.....
You can see a decrement and an increment in the value of quota and ID respectively. Present the next blank card again until the quota are used up or all card are formatted. Press ← to exit.	Quota: 99 ID: 0000000101

Configure Terminal Mode

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown.	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 2 to select the Set Prepaid / Bonus menu. It will prompt you to select prepaid or bonus mode.	Prepaid / Bonus Mode (1/2)?
Enter 1 to select Prepaid mode	TUE 07 SEP 15:46 Prepaid Terminal
Enter 2 to select Bonus mode.	TUE 07 SEP 15:46 Bonus Terminal

Mode of Expiry

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 3 to select the Set Expiry Mode menu.	Current Mode: NO EXPIRY
Press 1 to choose using server settings. Press 2 to set new expiry mode.	Server Settings? Yes/No (1/2)?
Press 1 to choose Yes.	Use Expiry Date Yes/No (1/2)?

To choose Fixed Month mode:

Press 1 to choose Fixed mode.	Fixed/ LastVisit Mode (1/2)?
Press 2 to choose absolute expiry month.	Relative / Abs. Month (1/2)?
Enter the expiry month by number and press Func to confirm.	1:Jan --> 12:Dec
It is done!	Done!

To choose the mode of Relative to Card Initialized Date:

Press 1 to choose Fixed mode.	Fixed/ LastVisit Mode (1/2)?
Press 1 to choose relative expiry month.	Relative / Abs. Month (1/2)?
Enter the number of month relative to the member card initialize date. Press Func to confirm.	No. of Months:
It is done!	Done!

To choose the mode of Automatic Expiry Extension Based on the time of last visit:

Press 2 to choose Fixed mode.	Fixed/ LastVisit Mode (1/2)?
Enter the number of month you want to extend for each member card transaction. Press Func to confirm.	#Extended Month
It is done!	Done!

Creating Staff Card

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 4 to select the Staff Card menu. Press 1 to create new staff card.	Create/Blacklist (1/2)?
Enter the maximum value of every single transaction that the staff is allowed. Press Func to confirm.	Max Transaction: \$1,000.00
Present a newly initialized card.	Create StaffCard Waiting Card...
It is done!	Done! ID: 0000000100

Blacklist Staff Card

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 4 to select the Staff Card menu. Press 2 to blacklist a staff card.	Create/Blacklist (1/2)?
Enter the staff ID, i.e. member ID of the staff card. Press Func to confirm.	Staff ID:
It is done!	Request Sent!

Network Settings

While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 5 to select the System Configuration menu. The current date is displayed. If necessary, enter the new date and then press the Func key to continue.	Date (M/D/Y): 09/07/2004
The current time is displayed. Enter the new time and press Func key	Time (H:M:S): 13:45:23
Enter the branch code. The value should be between 1 and 9999. Press the Func key to continue.	Branch Code: 1
Enter the terminal code. The value should be between 1 and 9999. Press the Func key to continue.	Terminal Code: 1
Enter IP address. Press the Func key to continue.	IP Address: 192.168.000.100
Enter sub net mask. Press the Func key to continue.	Subnetmask: 255.255.255.000
Enter gateway IP address. Press the Func key to continue.	Gateway: 192.168.000.200
Enter DNS IP address. Press the Func key to continue.	DNS: 192.168.000.200
Choose whether or not to connect to iBonus Server. Press 1 to choose yes. Press 2 to choose no. Press the Func key to keep the old setting.	Connect server? Y/N (1/2)?Y
If yes is chosen. Enter the server IP address. Press the Func key to continue.!	Server IP: 192.168.001.051
Enter server port. Default value should be 3080. Press the Func key to continue.	Server Port: 3080
Confirm the changes. Press 1 to commit changes. Press 2 or Func to discard changes.	OK to Accept Y/N (1/2)? No

Administrator Password	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 6 to select Set Password .	Set Password
Enter a new password. Press Func to re-enter password again.	Enter Password: ***
Press Func to save changes.	Reenter Password: ***
It is done!	Reenter Password: Updating...

Set Customer ID	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 8 to select the Assign Customer ID menu. Enter the member's ID and press Func .	Customer ID: 123
Present card.	123 Waiting Card...
It is done!	Member Card Updated OK!
Press Func to set another customer ID with an incremented value or enter any numbers to set manually.	Customer ID: 124
It is done!	Member Card Updated OK!

Set Bonus Rate	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Prepaid Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 0 to select the Set Bonus Rate menu.	Current Setting \$1 = 1 point
Enter 1 to use bonus point. Enter 2 otherwise.	Use Bonus Yes/No (1/2)?
You can see the new setting displayed as shown.	New Setting \$1 = 1 point

Master Card	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter B to select the Master Card menu. Enter 1 to read the information from master card. Enter 2 to fetch member card formatting quota.	Read Key/ Get Quota(1/2)? (1/2)?
If you choose 1 you can see the following screen. Present master card now.	Read MasterCard Waiting Card...
If you choose 2 you can see the following screen. Present master card now.	Get Quota Waiting Card...

System Reset and shutdown	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 7 to select the Shutdown/ Reset menu. Enter the member's ID and press Func . Press 1 if you wish to reset the access log.	Reset Log Yes/No (1/2)?
Enter 1 if you wish to reset the Terminal back to factory default. Please note that company code is still remaining in the Terminal while to card initialization quota will be reset to zero.	Factory Default Yes/No (1/2)?
Enter 2 if you wish to reset the card initialization quota.	Reset Quota Yes/No (1/2)?
If you wish to reboot the Terminal without resetting anything simply answer no in the three questions above.	Shutting Down

Deregister Terminal	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter 9 to select the De-register Terminal menu.	Deregister Terminal...
Press 1 to deregister the Terminal.	Are you sure Yes/No (1/2)?
Press ← if you wish to interrupt the deregistration process.	Send Transaction 15/100 done
If some transactions are not sent to server at the time when the ← is pressed, the following message is shown.	Transaction left 85
	Terminal not Deregistered

Internationalization	
While in Standby Mode, press the Func key to enter the Setup Menu. You will be prompted to enter the Administrator Password as shown	TUE 07 SEP 15:45 Bonus Terminal
Enter the Administrator Password and press Func (default password: 123).	Enter Password: ***
Enter A to select the Receipt Type menu. Default language is in English.	Default Language English
If there are additional languages available, simple select the language you wish to use.	Select Language: 1)Chinese, 2)Korean (1-2)?
Enter either 1 or 2 for the number of copies.	Number of Copies: (1/2)?
Enter 1 if you want to print the system configuration parameters.	Print Sys Config Yes/No (1/2)?



Lucky Technology Limited
 Flat C 2/F, Wah Hing Industrial Mansion,
 36 Tai Yau Street, San Po Kong, Kowloon, Hong Kong.
 e-mail: sales@lucky.com.hk web: www.lucky.com.hk
 ©Lucky Technology Ltd., 2007, All rights reserved